



FortiManager - Release Notes

Version 6.0.3

FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO GUIDE

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET COOKBOOK

<https://cookbook.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/support-and-training/training.html>

NSE INSTITUTE

<https://training.fortinet.com>

FORTIGUARD CENTER

<https://fortiguard.com/>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdocs@fortinet.com



November 13, 2018

FortiManager 6.0.3 Release Notes

02-603-519402-20181113

TABLE OF CONTENTS

FortiManager 6.0.3 Release	5
Supported models	5
What's new in FortiManager 6.0.3	6
System Settings	6
Special Notices	7
FortiManager 6.0.2 support for FortiOS 6.0.3	7
Reconfigure SD-WAN after Upgrade	7
FortiGate VM 16/32/UL license support	7
Hyper-V FortiManager-VM running on an AMD CPU	7
VM License (VM-10K-UG) Support	8
Recreate Guest List for Guest user group	8
FortiOS 5.4.0 Support	8
SSLv3 on FortiManager-VM64-AWS	8
Upgrade Information	9
Downgrading to previous firmware versions	9
Firmware image checksums	9
FortiManager VM firmware	9
SNMP MIB files	11
Product Integration and Support	12
FortiManager 6.0.3 support	12
Feature support	15
Language support	15
Supported models	16
FortiGate models	23
FortiCarrier models	25
FortiDDoS models	26
FortiAnalyzer models	26
FortiMail models	27
FortiSandbox models	28
FortiSwitch ATCA models	28
FortiWeb models	28
FortiCache models	29
FortiProxy models	30
FortiAuthenticator models	30
Compatibility with FortiOS Versions	31
FortiOS 6.0.3 compatibility issues	31
FortiOS 5.6.6 compatibility issues	31
FortiOS 5.6.4 compatibility issues	32
FortiOS 5.6.3 compatibility issues	32
FortiOS 5.6.0 and 5.6.1 compatibility issues	32
FortiOS 5.4.10 compatibility issues	33
FortiOS 5.4.9 compatibility issues	33

FortiOS 5.2.10 compatibility issues	33
FortiOS 5.2.7 compatibility issues	34
FortiOS 5.2.6 compatibility issues	34
FortiOS 5.2.1 compatibility issues	34
FortiOS 5.2.0 compatibility issues	34
Resolved Issues	36
Known Issues	39
Appendix A - FortiGuard Distribution Servers (FDS)	40
FortiGuard Center update support	40
Change Log	42

FortiManager 6.0.3 Release

This document provides information about FortiManager version 6.0.3 build 255.



The recommended minimum screen resolution for the FortiManager GUI is 1280 x 800. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 5](#)
- [What's new in FortiManager 6.0.3 on page 6](#)

Supported models

FortiManager version 6.0.3 supports the following models:

FortiManager	FMG-200D, FMG-200F, FMG-300D, FMG-300E, FMG-300F, FMG-400E, FMG-1000D, FMG-2000E, FMG-3000F, FMG-3900E, FMG-4000D, FMG-4000E, and FMG-MFGD.
FortiManager VM	FMG-VM64, FMG-VM64-AWS, FMG-VM64-Azure, FMG-VM64-GCP, FMG-VM64-HV (including Hyper-V 2016), FMG-VM64-KVM, FMG-VM64-OPC, FMG-VM64-XEN (for both Citrix and Open Source Xen).

What's new in FortiManager 6.0.3

The following is a list of new features and enhancements in 6.0.3. For details, see the *FortiManager Administrator Guide*:



Not all features/enhancements listed below are supported on all models

System Settings

Admin Profile - Device Lock and Permission improvement

Change to Admin Profile to allow granular permissions to be assigned per Device and Policy Package with ADOM unlocked, allowing administrators to execute scripts on the Devices & Policy Packages.

Special Notices

This section highlights some of the operational changes that administrators should be aware of in 6.0.3.

FortiManager 6.0.2 support for FortiOS 6.0.3

FortiManager 6.0.2 treats the `status` field of firewall policies as a mandatory field, and it is set to `enable` by default. FortiOS 6.0.3 has reverted this change. As a result, FortiManager may report verification failures on installations. The verification report shows that the policy `status` field has to be installed with the `enable` setting:

```
"---> generating verification report
      (vdom root: firewall policy 1:status)
      remote original:
      to be installed: enable

<--- done generating verification report

install failed"
```

Reconfigure SD-WAN after Upgrade

The SD-WAN module has been fully redesigned in FortiManager v6.0 to provide granular monitor and control. Upgrading SD-WAN settings from 5.6 to 6.0 is not supported. Please reconfigure SD-WAN after upgraded to v6.0.

FortiGate VM 16/32/UL license support

FortiOS 5.4.4 introduces new VM license types to support additional vCPUs. FortiManager 5.6.0 supports these new licenses with the prefixes of FGVM16, FGVM32, and FGVMUL.

Hyper-V FortiManager-VM running on an AMD CPU

A Hyper-V FMG-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

VM License (VM-10K-UG) Support

FortiManager 5.4.2 introduces a new VM license (VM-10K-UG) that supports 10,000 devices. It is recommended to upgrade to FortiManager 5.4.2 or later before applying the new license to avoid benign GUI issues.

Recreate Guest List for Guest user group

After upgrading to FortiManager 6.0.3, recreate the guest list for the *Guest* user group in ADOM Policy Object before installing device settings to FortiGate devices. For more information, see Bug ID 499568 in *Resolved Issues*.

FortiOS 5.4.0 Support

With the enhancement in password encryption, FortiManager 5.4.2 and later no longer supports FortiOS 5.4.0. Please upgrade FortiGate to 5.4.2 or later.



The following ADOM versions are not affected: 5.0 and 5.2.

SSLv3 on FortiManager-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiManager-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
set ssl-protocol tlsv1
end
```


Upgrade Information

You can upgrade FortiManager 5.6.0 or later directly to 6.0.3. If you are upgrading from versions earlier than 5.6.x, you should upgrade to the latest patch version of FortiManager 5.6, then 6.0.0.



For details about upgrading your FortiManager device, see the *FortiManager Upgrade Guide*.

This section contains the following topics:

- [Downgrading to previous firmware versions on page 9](#)
- [Firmware image checksums on page 9](#)
- [FortiManager VM firmware on page 9](#)
- [SNMP MIB files on page 11](#)

Downgrading to previous firmware versions

FortiManager does not provide a full downgrade path. You can downgrade to a previous firmware release via the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrading process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format {disk | disk-ext4 | disk-ext3}
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in select *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

FortiManager VM firmware

Fortinet provides FortiManager VM firmware images for Amazon AWS, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Google GCP

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.gcp.zip`: Download the 64-bit package for a new FortiManager VM installation.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `FMG_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.
- `.hyperv.zip`: Download the package for a new FortiManager VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Azure.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `FMG_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.
- `.hyperv.zip`: Download the package for a new FortiManager VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

VMware ESX/ESXi

- `.out`: Download the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the FortiManager product data sheet available on the Fortinet web site, <http://www.fortinet.com/products/fortimanager/virtualappliances.html>. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiManager version 5.00 file folder.

Product Integration and Support

This section lists FortiManager 6.0.3 support of other Fortinet products. It also identifies what FortiManager features are supported for managed platforms and what languages FortiManager supports. It also lists which Fortinet models can be managed by FortiManager.

The section contains the following topics:

- [FortiManager 6.0.3 support on page 12](#)
- [Feature support on page 15](#)
- [Language support on page 15](#)
- [Supported models on page 16](#)

FortiManager 6.0.3 support

The following table lists 6.0.3 product integration and support information:

Web Browsers	<ul style="list-style-type: none">• Microsoft Internet Explorer version 11 or Edge 40 Due to limitation on Microsoft Internet Explorer or Edge, it may not completely render a page with a large set of policies or objects.• Mozilla Firefox version 61• Google Chrome version 68 <p>Other web browsers may function correctly, but are not supported by Fortinet.</p>
FortiOS/FortiOS Carrier	<ul style="list-style-type: none">• 6.0.0 to 6.0.3 FortiManager 6.0.2 is fully tested as compatible with FortiOS/FortiOS Carrier 6.0.3, with some minor interoperability issues. For information, see FortiOS 6.0.3 compatibility issues on page 31.• 5.6.5 to 5.6.6 FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.6, with some minor interoperability issues. For information, see FortiOS 5.6.6 compatibility issues on page 31.• 5.6.4 FortiManager 5.6.3 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.4, with some minor interoperability issues. For information, see FortiOS 5.6.4 compatibility issues on page 32.• 5.6.2 to 5.6.3 FortiManager 5.6.1 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.2 to 5.6.3, with some minor interoperability issues. For information, see FortiOS 5.6.3 compatibility issues on page 32.• 5.6.0 to 5.6.1 FortiManager 5.6.0 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.0 to 5.6.1, with some minor interoperability issues. For

information, see [FortiOS 5.6.0 and 5.6.1 compatibility issues on page 32](#).

- 5.4.10
FortiManager 5.4.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.4.10, with some minor interoperability issues. For information, see [FortiOS 5.4.10 compatibility issues on page 33](#).
- 5.4.9
FortiManager 5.6.3 is fully tested as compatible with FortiOS/FortiOS Carrier 5.4.9, with some minor interoperability issues. For information, see [FortiOS 5.4.9 compatibility issues on page 33](#).
- 5.4.1 to 5.4.8
- 5.2.8 to 5.2.13
FortiManager 5.4.1 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.10, with some minor interoperability issues. For information, see [FortiOS 5.2.10 compatibility issues on page 33](#).
- 5.2.7
FortiManager 5.2.6 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.7, with some minor interoperability issues. For information, see [FortiOS 5.2.7 compatibility issues on page 34](#).
- 5.2.6
FortiManager 5.2.4 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.6, with some minor interoperability issues. For information, see [FortiOS 5.2.6 compatibility issues on page 34](#).
- 5.2.2 to 5.2.5
- 5.2.1
FortiManager 5.2.1 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.1, with some minor interoperability issues. For information, see [FortiOS 5.2.1 compatibility issues on page 34](#).
- 5.2.0
FortiManager 5.2.1 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.0, with some minor interoperability issues. For information, see [FortiOS 5.2.0 compatibility issues on page 34](#).

FortiAnalyzer

- 6.0.0 and later
- 5.6.0 and later
- 5.4.0 and later
- 5.2.0 and later
- 5.0.0 and later

FortiAuthenticator

- 5.2.2

FortiCache

- 4.2.7
- 4.2.6
- 4.1.2
- 4.0.0 to 4.0.4

FortiClient

- 5.6.6
- 5.6.3
- 5.6.0

	<ul style="list-style-type: none"> • 5.4.0 and later • 5.2.0 and later
FortiMail	<ul style="list-style-type: none"> • 5.4.5 • 5.3.12 • 5.2.10 • 5.1.7 • 5.0.10
FortiSandbox	<ul style="list-style-type: none"> • 2.5.0 to 2.5.2 • 2.4.0 and 2.4.1 • 2.3.2 and 2.3.3 • 2.2.2 • 2.1.3 • 1.4.0 and later • 1.3.0 • 1.2.0 and later
FortiSwitch ATCA	<ul style="list-style-type: none"> • 5.2.3 • 5.0.0 and later • 4.3.0 and later • 4.2.0 and later
FortiWeb	<ul style="list-style-type: none"> • 5.9.1 • 5.8.6 • 5.8.3 • 5.8.1 • 5.8.0 • 5.7.2 • 5.6.1 • 5.5.6 • 5.4.1 • 5.3.9 • 5.2.4 • 5.1.4 • 5.0.6
FortiDDoS	<ul style="list-style-type: none"> • 4.5.0 • 4.4.1 • 4.2.3 • 4.1.11 <p>Limited support. For more information, see Feature support on page 15.</p>
Virtualization	<ul style="list-style-type: none"> • Amazon Web Service AMI, Amazon EC2, Amazon EBS • Citrix XenServer 7.2 • Linux KVM Redhat 7.1 • Microsoft Azure • Microsoft Hyper-V Server 2012 and 2016 • OpenSource XenServer 4.2.5 • VMware ESXi versions 5.0, 5.5, 6.0, 6.5 and 6.7



To confirm that a device model or firmware version is supported by current firmware version running on FortiManager, run the following CLI command:

```
diagnose dvm supported-platforms list
```



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Feature support

The following table lists FortiManager feature support for managed platforms.

Platform	Management Features	FortiGuard Update Services	Reports	Logging
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiAnalyzer	•	•	✓	✓
FortiAuthenticator	•	•	✓	✓
FortiCache	•	•	✓	✓
FortiClient	•	✓	✓	✓
FortiDDoS	•	•	✓	✓
FortiMail	•	✓	✓	✓
FortiSandbox	•	✓	✓	✓
FortiSwitch ATCA	✓	•	•	•
FortiWeb	•	✓	✓	✓
Syslog	•	•	•	✓

Language support

The following table lists FortiManager language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓

Language	GUI	Reports
Chinese (Traditional)	✓	✓
French	•	✓
Japanese	✓	✓
Korean	✓	✓
Portuguese	•	✓
Spanish	•	✓

To change the FortiManager language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiManager, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiManager. For more information, see the *FortiAnalyzer Administration Guide*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch ATCA, FortiWeb, FortiCache, FortiProxy, and FortiAuthenticator models and firmware versions that can be managed by a FortiManager or send logs to a FortiManager running version 6.0.3.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 23](#)
- [FortiCarrier models on page 25](#)
- [FortiDDoS models on page 26](#)
- [FortiAnalyzer models on page 26](#)
- [FortiMail models on page 27](#)
- [FortiSandbox models on page 28](#)
- [FortiSwitch ATCA models on page 28](#)
- [FortiWeb models on page 28](#)
- [FortiCache models on page 29](#)
- [FortiProxy models on page 30](#)
- [FortiAuthenticator models on page 30](#)

FortiGate models

Model	Firmware Version
<p>FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600D, FG-800D, FG-900D, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3600C, FG3700D, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E</p> <p>FortiGate 5000 Series: FG-5001D, FG-5001E, FG-5001E1</p> <p>FortiGate DC: FG1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC</p> <p>FortiGate Hardware Low Encryption: FG-100D-LENC, FG-600C-LENC</p> <p>Note: All license-based LENC is supported based on the FortiGate support list.</p> <p>FortiWiFi: FWF-30D, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-90D, FWF-90D-POE, FWF-92D</p> <p>FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-AZUREONDEMAND, FG-VM64-Azure, FG-VM64-GCP, VM64-GCPONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM, FOS-VM64-Xen</p> <p>FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D</p>	6.0
<p>FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-60E-DSL, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E,</p> <p>FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1</p> <p>FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC</p> <p>FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC</p> <p>Note: All license-based LENC is supported based on the FortiGate support list.</p> <p>FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D</p>	5.6

Model	Firmware Version
FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-Azure, FG-VM64-AZUREONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D	
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E, FG-2000E, FG-2500E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8 FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	5.4
FortiGate: FG-20C, FG-20C-ADSL-A, FG-30D, FG-30D-POE, FG-40C, FG-60C, FG-60C-POE, FG-60C-SFP, FG-60D, FG-60D-3G4G-VZW, FG-60D-POE, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-90D, FG-90D-POE, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-110C, FG-111C, FG-140D, FG-140D-POE, FG-140D-POE-T1, FG-200B, FG-200B-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-300C, FG-300D, FG-310B, FG-311B, FG-400D, FG-500D, FG-600C, FG-600D, FG-620B, FG-621B, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1240B, FG-1500D, FG-1500DT, FG-3000D, FG-3016B, FG-3040B, FG-3100D, FG-3140B, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3810A, FG-3810D, FG-3815D, FG-3950B, FG-3951B	5.2

Model	Firmware Version
FortiGate 5000 Series: FG-5001A, FG-5001A-SW, FG-5001A-LENC, FG-5001A-DW-LENC, FG-5001A-SW-LENC, FG-5001B, FG-5001C, FG-5001D, FG-5101C FortiGate DC: FG-80C-DC, FG-300C-DC, FG-310B-DC, FG-600C-DC, FG-620B-DC, FG-621B-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1240B-DC, FG-1500D-DC, FG-3000D-DC, FG-3040B-DC, FG-3100D-DC, FG-3140B-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, G-3700D-DC, FG-3810A-DC, FG-3810D-DC, FG-3815D-DC, FG-3950B-DC, FG-3951B-DC FortiGate Low Encryption: FG-20C-LENC, FG-40C-LENC, FG-60C-LENC, FG-80C-LENC, FG-100D-LENC, FG-200B-LENC, FG-300C-LENC, FG-310B-LENC, FG-600C-LENC, FG-620B-LENC, FG-1000C-LENC, FG-1240B-LENC, FG-3040B-LENC, FG-3140B-LENC, FG-3810A-LENC, FG-3950B-LENC FortiWiFi: FWF-20C, FWF-20C-ADSL-A, FWF-30D, FWF-30D-POE, FWF-40C, FWF-60C, FWF-60CM, FWF-60CX-ADSL-A, FWF-60D, FWF-60D-3G4G-VZW, FWF-60D-POE, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate Rugged: FGR-60D, FGR-100C FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWSONDEMAND, FG-VM-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN FortiSwitch: FS-5203B, FCT-5902D	

FortiCarrier Models

Model	Firmware Version
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3700D, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001D, FGT-5001E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001C, FGT-5001D, FGT-5001E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-5001C, FGT-5001D, FGT-7030E, FGT-7040E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC	

Model	Firmware Version
FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, , FGT-3810A, FGT-3810D, FGT-3950B, FGT-3951B, FGT-5100B, FGT-5100C, FGT-5001D, FGT-5101C, FS-5203B, FT-5902D	5.2
FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3810A-DC, FGT-3810D-DC, FGT-3950B-DC, FGT-3951B-DC	
FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-Xen	

FortiDDoS models

Model	Firmware Version
FortiDDoS: FI-200B, FI400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B, FI-3000B	4.2, 4.1, 4.0

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E.	5.6
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-AWS, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B.	5.4
FortiAnalyzer VM: FAZ-VM64, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B	5.2
FortiAnalyzer VM: FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B	5.0
FortiAnalyzer VM: FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM-KVM, FAZ-VM-XEN	

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B FortiMail Low Encryption: FE-3000C-LENC FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3.7
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2.8
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.1.6
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.0.10

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-VM	2.4.0 2.3.2
FortiSandbox: FSA-1000D, FSA-3000D, FSA-3500D FortiSandbox VM: FSA-VM	2.2.0 2.1.0
FortiSandbox: FSA-1000D, FSA-3000D FortiSandbox VM: FSA-VM	2.0.0 1.4.2
FortiSandbox: FSA-1000D, FSA-3000D	1.4.0 and 1.4.1 1.3.0 1.2.0 and later

FortiSwitch ACTA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-5913C	5.2.0
FortiSwitch-ATCA: FS-5003A, FS-5003B FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.0.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3.0 4.2.0

FortiWeb models

Model	Firmware Version
FortiWeb: FWB-2000E	5.6.0
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E	5.5.3
FortiWeb VM: FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV, FWB-KVM, FWB-AZURE	
FortiWeb: FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.4.1
FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV	
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.3.8
FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.2.4
FortiWeb VM: FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E	4.0
FortiCache VM: FCH-VM64	

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-2000E	1.0
FortiProxy VM: FPX-KVM, FPX-VM64	

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-3000B, FAC-3000D, FAC-3000E, FAC-VM	4.0 and 4.1

FortiGate models

Model	Firmware Version
<p>FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600D, FG-800D, FG-900D, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3600C, FG3700D, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E</p> <p>FortiGate 5000 Series: FG-5001D, FG-5001E, FG-5001E1</p> <p>FortiGate DC: FG1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC</p> <p>FortiGate Hardware Low Encryption: FG-100D-LENC, FG-600C-LENC</p> <p>Note: All license-based LENC is supported based on the FortiGate support list.</p> <p>FortiWiFi: FWF-30D, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-90D, FWF-90D-POE, FWF-92D</p> <p>FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-AZUREONDEMAND, FG-VM64-Azure, FG-VM64-GCP, VM64-GCPONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM, FOS-VM64-Xen</p> <p>FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D</p>	6.0
<p>FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-60E-DSL, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E,</p> <p>FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1</p>	5.6

Model	Firmware Version
FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-Azure, FG-VM64-AZUREONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D	
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG 3800D, FG-3810D, FG-3815D, FG-3960E, FG3980E, FG-2000E, FG-2500E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8 FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	5.4

Model	Firmware Version
FortiGate: FG-20C, FG-20C-ADSL-A, FG-30D, FG-30D-POE, FG-40C, FG-60C, FG-60C-POE, FG-60C-SFP, FG-60D, FG-60D-3G4G-VZW, FG-60D-POE, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-90D, FG-90D-POE, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-110C, FG-111C, FG-140D, FG-140D-POE, FG-140D-POE-T1, FG-200B, FG-200B-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-300C, FG-300D, FG-310B, FG-311B, FG-400D, FG-500D, FG-600C, FG-600D, FG-620B, FG-621B, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1240B, FG-1500D, FG-1500DT, FG-3000D, FG-3016B, FG-3040B, FG-3100D, FG-3140B, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3810A, FG-3810D, FG-3815D, FG-3950B, FG-3951B FortiGate 5000 Series: FG-5001A, FG-5001A-SW, FG-5001A-LENC, FG-5001A-DW-LENC, FG-5001A-SW-LENC, FG-5001B, FG-5001C, FG-5001D, FG-5101C FortiGate DC: FG-80C-DC, FG-300C-DC, FG-310B-DC, FG-600C-DC, FG-620B-DC, FG-621B-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1240B-DC, FG-1500D-DC, FG-3000D-DC, FG-3040B-DC, FG-3100D-DC, FG-3140B-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3810A-DC, FG-3810D-DC, FG-3815D-DC, FG-3950B-DC, FG-3951B-DC FortiGate Low Encryption: FG-20C-LENC, FG-40C-LENC, FG-60C-LENC, FG-80C-LENC, FG-100D-LENC, FG-200B-LENC, FG-300C-LENC, FG-310B-LENC, FG-600C-LENC, FG-620B-LENC, FG-1000C-LENC, FG-1240B-LENC, FG-3040B-LENC, FG-3140B-LENC, FG-3810A-LENC, FG-3950B-LENC FortiWiFi: FWF-20C, FWF-20C-ADSL-A, FWF-30D, FWF-30D-POE, FWF-40C, FWF-60C, FWF-60CM, FWF-60CX-ADSL-A, FWF-60D, FWF-60D-3G4G-VZW, FWF-60D-POE, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate Rugged: FGR-60D, FGR-100C FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWSONDEMAND, FG-VM-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN FortiSwitch: FS-5203B, FCT-5902D	5.2

FortiCarrier models

Model	Firmware Version
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3700D, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001D, FGT-5001E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	6.0
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001C, FGT-5001D, FGT-5001E	5.6

Model	Firmware Version
FortiCarrier-DC: FGT-3000D-DC, FGC-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-5001C, FGT-5001D, FGT-7030E, FGT-7040E FortiCarrier-DC: FGT-3000D-DC, FGC-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	5.4
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, , FGT-3810A, FGT-3810D, FGT-3950B, FGT-3951B, FGT-5100B, FGT-5100C, FGT-5001D, FGT-5101C, FS-5203B, FT-5902D FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3810A-DC, FGT-3810D-DC, FGT-3950B-DC, FGT-3951B-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-Xen	5.2

FortiDDoS models

Model	Firmware Version
FortiDDoS: FI-200B, FI400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B, FI-3000B	4.2, 4.1, 4.0

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E. FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-AWS, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	5.6

Model	Firmware Version
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B. FortiAnalyzer VM: FAZ-VM64, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	5.4
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	5.2
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	5.0

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000E, FE-3200E FortiMail Low Encryption: FE-3000C-LENC	5.4.5
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B FortiMail Low Encryption: FE-3000C-LENC FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3.12
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2.10
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.1.7
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.0.10

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-KVM, FSA-VM	2.5.2
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-VM	2.4.1 2.3.3
FortiSandbox: FSA-1000D, FSA-3000D, FSA-3500D FortiSandbox VM: FSA-VM	2.2.0 2.1.3
FortiSandbox: FSA-1000D, FSA-3000D FortiSandbox VM: FSA-VM	2.0.3 1.4.2
FortiSandbox: FSA-1000D, FSA-3000D	1.4.0 and 1.4.1 1.3.0 1.2.0 and later

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-5913C	5.2.0
FortiSwitch-ATCA: FS-5003A, FS-5003B FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.0.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3.0 4.2.0

FortiWeb models

Model	Firmware Version
FortiWeb: FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.9.1
FortiWeb: FWB-1000C, FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-Azure-Ondemand, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.8.6

Model	Firmware Version
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-OS1, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.7.2
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.6.1
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV, FWB-KVM, FWB-AZURE	5.5.6
FortiWeb: FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV	5.4.1
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	5.3.9
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	5.2.4

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64	4.0

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-2000E FortiProxy VM: FPX-KVM, FPX-VM64	1.0

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-3000B, FAC-3000D, FAC-3000E, FAC-VM	4.0 and 4.1

Compatibility with FortiOS Versions

This section highlights compatibility issues that administrators should be aware of in FortiManager 6.0.3. Compatibility issues have been identified for the following FortiOS releases:

FortiOS 6.0	FortiOS 6.0.3 compatibility issues on page 31
FortiOS 5.6	FortiOS 5.6.6 compatibility issues on page 31
	FortiOS 5.6.4 compatibility issues on page 32
	FortiOS 5.6.3 compatibility issues on page 32
	FortiOS 5.6.0 and 5.6.1 compatibility issues on page 32
FortiOS 5.4	FortiOS 5.4.10 compatibility issues on page 33
	FortiOS 5.4.9 compatibility issues on page 33
FortiOS 5.2	FortiOS 5.2.10 compatibility issues on page 33
	FortiOS 5.2.7 compatibility issues on page 34
	FortiOS 5.2.6 compatibility issues on page 34
	FortiOS 5.2.1 compatibility issues on page 34
	FortiOS 5.2.0 compatibility issues on page 34

FortiOS 6.0.3 compatibility issues

The following table lists known interoperability issues that have been identified with FortiManager version 6.0.2 and FortiOS version 6.0.3.

Bug ID	Description
516113	Install verification may fail on policy status field. For details, see the following Special Notice: FortiManager 6.0.2 support for FortiOS 6.0.3 on page 7 .
516242	Install verification may fail on the wtp profile's <code>handoff-sta-thresh</code> parameter.

FortiOS 5.6.6 compatibility issues

The following table lists known interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS version 5.6.6.

Bug ID	Description
513066	FortiManager 5.6.5 does not support the following new value in FortiOS 5.6.6: <code>system sdn-connector</code> command with the <code>azure-region</code> variable set to <code>germany usgov local</code> . If set on FortiGate, the values will be unset during the next configuration installation from FortiManager.
513069	FortiManager 5.6.5 does not support the following new value in FortiOS 5.6.6: <code>system snmp user</code> command with the <code>community events</code> variable set to <code>av-oversize-blocked</code> or <code>faz-disconnect</code> . If set on FortiGate, the values will be unset during the next configuration installation from FortiManager.

FortiOS 5.6.4 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.6.3 and FortiOS 5.6.4.

Bug ID	Description
486921	FortiManager may not be able to support the syntax for the following objects: <ul style="list-style-type: none">• <code>rsso-endpoint-block-attribute</code>, <code>rsso-endpoint-block-attribute</code>, or <code>sso-attribute</code> for RADIUS users.• <code>sdn</code> and its <code>filter</code> attributes for firewall address objects.• <code>azure</code> SDN connector type.• <code>ca-cert</code> attribute for LDAP users.

FortiOS 5.6.3 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.6.1 and FortiOS 5.6.3.

Bug ID	Description
469993	FortiManager has a different default value for <code>switch-controller-dhcp-snooping</code> from that on FortiGate.

FortiOS 5.6.0 and 5.6.1 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.6.0 and FortiOS 5.6.0 and 5.6.1.

Bug ID	Description
451036	FortiManager may return verification error on <code>proxy enable</code> when installing a policy package.
460639	FortiManager may return verification error on <code>wtp-profile</code> when creating a new VDOM.

FortiOS 5.4.10 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.4.5 and FortiOS 5.4.10.

Bug ID	Description
508337	FortiManager cannot edit the following configurations for replacement message: <ul style="list-style-type: none">• <code>system replacemsg mail "email-decompress-limit"</code>• <code>system replacemsg mail "smtp-decompress-limit"</code>• <code>system replacemsg nntp "email-decompress-limit"</code>

FortiOS 5.4.9 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.6.3 and FortiOS 5.4.9.

Bug ID	Description
486592	FortiManager may report verification failure on the following attributes for RADIUS users: <code>rsso-endpoint-attribute</code> <code>rsso-endpoint-block-attribute</code> <code>sso-attribute</code>

FortiOS 5.2.10 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.4.1 and FortiOS 5.2.10.

Bug ID	Description
397220	FortiOS 5.2.10 increased the maximum number of the firewall schedule objects for 1U and 2U+ appliances. As a result, a retrieve may fail if more than the maximum objects are configured.

FortiOS 5.2.7 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.2.6 and FortiOS 5.2.7.

Bug ID	Description
365757	Retrieve may fail on LDAP User Group if object filter has more than 511 characters.
365766	Retrieve may fail when there are more than 50 portals within a VDOM.
365782	Install may fail on system global optimize or system fips-cc entropy-token.

FortiOS 5.2.6 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.2.4 and FortiOS 5.2.6.

Bug ID	Description
308294	1) New default wtp-profile settings on FOS 5.2.6 cause verification errors during installation. 2) FortiManager only supports 10,000 firewall addresses while FortiOS 5.2.6 supports 20,000 firewall addresses.

FortiOS 5.2.1 compatibility issues

The following table lists interoperability issues that have been identified with FortiManager version 5.2.1 and FortiOS version 5.2.1.

Bug ID	Description
262584	When creating a VDOM for the first time it fails.
263896	If it contains the certificate: <code>Fortinet_CA_SSLProxy</code> or <code>Fortinet_SSLProxy</code> , retrieve may not work as expected.

FortiOS 5.2.0 compatibility issues

The following table lists known interoperability issues that have been identified with FortiManager version 5.2.1 and FortiOS version 5.2.0.

Bug ID	Description
262584	When creating a VDOM for the first time it fails.
263949	Installing a VIP with port forwarding and ICMP to a 5.2.0 FortiGate fails.

Resolved Issues

The following issues have been fixed in 6.0.3. For inquiries about a particular bug, please contact [Customer Service & Support](#).

Bug ID	Description
304522	Wildcard admin is unable to approve a workflow session.
413390	FGFM connection flapping when FortiGate is moved to another ADOM.
423921	Cannot get CSF group name.
434984	Unable to create/edit/delete ADOMs when system setting is read only.
439512	FortiManager attempts to delete user groups that are used only under system admin, if not defined in the management VDOM.
450434	The "wtp-mode" option is unset after change of AP config from AP Manager.
451684	List all conflicting Global assigned objects in Import Wizard and report.
453417	Import of PKCS #12 local certificate failed.
474629	When Security Profile Groups are created on FortiManager, all Security Profile Groups are pushed to all FortiGate units on next policy push.
480400	Device Manager > System Information does not display correct FortiGate system time.
481901	Add a CLI command to reset hitcount for all ADOMs and dbcach.
485859	Should remove Botnet from Application Control for 5.6/6.0 ADOMs.
491926	Rename ADOM interface during Import Policy may fail to add policy.
492893	Installing custom IPS and <i>AppCtl</i> signatures with the same Attack ID will fail installation or not function correctly on FortiGate.
494108	When adding an interface to a zone, the <i>Block intra-zone traffic</i> option is unset.
494253	Some service objects are not visible in GUI of specific ADOMs when backend has invalid service config.
499053	Wrong interface-pair view for Proxy Policy.
499066	Can't verify PKI admin client certificate, if the CA chain has more than 2 certificates.
499341	A new LDAP admin user with GUI access is using an admin profile of a previously created LDAP admin user.
499568	Missing Guest Management support in FortiManager Policy & Objects tab.
500480	After editing an address that is used in an address group, the status did not change for 'Policy Package Status'.
501096	Policy package status of all devices going in Modified state when policy package is imported for

Bug ID	Description
	new devices.
501467	Application fgdsrv crashes several times per day - parseFragment: url index out of range.
501485	ADOM upgrade from 5.4 to 5.6 tries to change 'Web Filter Local Category' ID from 179 to 192.
503072	Application crond crashes are caused by hitcount updates.
504394	AP Manager - WiFi profile FAP221E does not display RADIO 2 option.
504422	Install verification fails after FortiGate HA failover due to vdom-link macaddr mismatch.
504541	Page is not loading properly for AP profiles under AP Manager in 5.2 ADOM.
504636	Some address objects are not visible in GUI of specific ADOMs when backend has invalid address config.
504999	Install SD-WAN static route to FortiGate failed.
505004	Columns overlap in policy list page.
505276	VPN Monitor stuck loading for 5.2/5.4 ADOMs.
507075	Upgrade of ADOM 'root' from 5.6 to 6.0 hangs and crashes <i>svc cdb reader</i> .
507092	FortiManager cannot show 1 ADOM interface page when interface dynamic mapping is missing device information.
507300	FortiManager should not download the FortiGate delta package from FortiGuard.
507394	FortiManager displays the "Error:response with errors" error when creating a new script that is over the tablesize limit.
507628	After successful installation, device config status may show as out of sync or modified or conflict
507919	Need to import firewall internet-service-custom, although it is not directly used by firewall policy.
508810	Administrative Distance is missing for Static Route with Destination type Named Address.
509173	Policy package installation for root ADOM fails after upgrading from 5.4.5 to 5.6.4.
509185	FortiManager installs default certificate instead of dynamically mapped certificate that is used in dynamically mapped virtual server.
509769	5.4 ADOM cannot assign profile to FAP221.
509854	If firewall address groups are recursively defined (for example, its member contains itself), this causes the security console to crash.
510641	Edit policy and click OK. The table scrolls back to top.
510910	When a new object is created from an IPv4 policy, the previous content of the related field is cleared.
510929	GUI Import wizard should display "Renamed Objects" before importing objects.
510936	Adding a new device to address object dynamic mapping sets the interface to 'any' for previous associated devices.

Bug ID	Description
511170	FortiAnalyzer/Fortimanager cannot sync with some NTP servers.
511753	SNMP event power-supply-failure is missing for some devices.
512350	<code>system.ha.hbdev</code> will not always save. This is applicable to CLI only.
513243	On the device level interface config page, the allow access config cannot disable HTTP.
513255	GUI slowness is caused by viewing, editing, or cloning IPsec phase1/phase2 in Device Manager.
514300	The log <i>FortiAnalyzer filter</i> setting cannot be retrieved or configured on FortiManager.
516789	Fabric Connector for VMWare NSX not importing any object and displays error message 'Internal Error' for NSX version 6.3.3.
516889	FortiManager will use FortiGuard update for FortiGate certificate bundle support.
517204	Add/Retrieve fails with "data not exist" if "external-resource" category is used in "ftgd-dns filters" in DNS filter.
517235	Device Manager System DHCP Server Lease Time changes not editable via GUI.
517243	Refreshing "Policy & Objects" pane clears the "Last Modified" tab on the policies.
517533	Cannot specify more than one DNS server in AP Manager SSID profile.
518668	Inconsistent user-database options when configuring a local Authentication Scheme.
519188	RADIUS VSA attributes can be used to gain read-write access to all ADOMs.
519206	Web Server Error 500 when trying to filter device Session List.

Known Issues

The following issues have been identified in 6.0.3. For inquiries about a particular bug or to report a bug, please contact [Customer Service & Support](#).

Bug ID	Description
478257	VPN Manager should filter out invalid interfaces for the default VPN interface.
501202	AP Manager Wifi profiles missing LAN ports configuration settings on FortiManager GUI.
507629	Clicking the Cancel button in the Install wizard causes task errors.
510663	Despite the FDS proxy settings, FortiManager is attempting to connect directly to the productapi.fortinet.com.
517232	Invalid Source/Destination "Negate Cell" option for certain policy types and missing "Negate Cell" for IPv4 policy source address.
518680	IP Pool not imported due to error create mapping fail related to "arp-intf" which is a members of a zone setting in ippool.
519108	Scheduled Remote CLI Scripts are stuck at 1%.
520899	When editing the Address Group Dynamic mapping configuration entry for the second time, the GUI will show an empty member list. Close the address group configuration page and re-edit the mapping entry as a first time edit.
522310	B255: Unable to edit Global ADOM DB to change global version from GUI.
523156	GUI failed to create or edit SSL VPN portal profile in 5.2, 5.4, and 5.6 ADOMs.

Appendix A - FortiGuard Distribution Servers (FDS)

In order for the FortiManager to request and retrieve updates from FDS, and for FortiManager to serve as a FDS, please configure the necessary settings on all devices between FortiManager and FDS, or between FortiManager and FortiGate devices based on the items listed below:

- FortiManager accesses FDS for antivirus and attack updates through TCP/SSL port 443.
- If there is a proxy server between FortiManager and FDS, FortiManager uses port 80 to communicate with the proxy server by default and connects to the proxy server using HTTP protocol.
- If FortiManager manages a FortiGate device located behind a proxy server, the proxy server permits TCP/SSL traffic to pass through via port 443.

FortiGuard Center update support

You can configure FortiManager as a local FDS to provide FortiGuard updates to other Fortinet devices and agents on your network. The following table lists which updates are available per platform/version:

Platform	Version	Antivirus	WebFilter	Vulnerability Scan	Software
FortiClient (Windows)	• 6.0.0 and later	✓	✓	✓	✓
FortiClient (Windows)	• 5.6.0 and later • 5.4.0 and later	✓	•	✓	•
FortiClient (Mac OS X)	• 6.0.0 and later • 5.6.0 and later • 5.4.0 and later	✓	•	✓	•
FortiMail	• 5.4.5 • 5.4.2 • 4.3.7 • 4.2.9 • 5.1.6	✓	•	•	•
FortiSandbox	• 2.5.0, 2.5.1 • 2.4.0, 2.4.1 • 2.3.2 • 2.2.1 • 2.1.2 • 1.4.0 and later • 1.3.0 • 1.2.0, 1.2.3	✓	•	•	•
FortiWeb	• 5.9.0	✓	•	•	•

Platform	Version	Antivirus	WebFilter	Vulnerability Scan	Software
	<ul style="list-style-type: none">• 5.8.6• 5.6.0• 5.5.4• 5.4.1• 5.3.8• 5.2.4• 5.1.4• 5.0.6				



To enable FortiGuard Center updates for FortiMail version 4.2 enter the following CLI command:


```
config fmupdate support-pre-fgt-43
set status enable
end
```

Change Log

Date	Change Description
2018-11-02	Initial release of 6.0.3.
2018-11-07	Added FMG-VM64-GCP to <i>Supported Models</i> .
2018-11-09	Resolved issues added (423921, 512350). Special notice added for Resolved Issue 499568 in the Special Notices section. Known Issue added (523156).
2018-11-13	Added a Known Issue (520899).



FORTINET®



Copyright© 2018 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.